

PD990096

Search mode for a D-VHS recorder**BACKGROUND OF THE INVENTION**

5 The invention relates to a search mode in a video recorder according to the helical scan method, in particular a video recorder in accordance with the D-VHS system standard, which enables both the recording and/or reproduction of analogue and the recording and/or reproduction of digital television signals by means of magnetic tape cassettes.

10 The D-VHS system has the advantage that it is compatible with the VHS system, in which case (in particular with the recording of CTL (control) pulses in a longitudinal track of the recording medium also for the recording of digital television signals) head drum and tape drive servos can be applied to both systems. In contrast to the VHS system, however, according to which in each case two slanted tracks are provided for recording a frame, recording digital data in accordance with the D-VHS system standard for recovering a frame can encompass in each case up to six slanted tracks.

20 The consequence of this for signal recordings, however, is that a position to be sought on the recording medium using CTL pulses can be moved to only with an accuracy which is possible on the basis of the CTL pulse frequency and has proved successful for searching for recorded analogue television signals.

30 With regard to recorded digital television signals, however, a greater search accuracy is desirable - particularly when these signals are intended to be edited.

35

SUMMARY OF THE INVENTION

 The object of the invention is to improve the search mode in a video recorder for recorded digital television signals, the said video recorder's system

standard for digital signal recordings being compatible with the system standard for analogue signal recordings.

This object is achieved by means of a method
5 specified in claim 1 and by means of a video recorder specified in claim 7.

The invention is based on the idea of carrying out the search for a recorded digital television signal with reference to a track-accurate tape position as
10 absolute start position preferably at rewind speed using an evaluation of CTL pulses and, upon reaching the target position or in the vicinity thereof, of automatically completing the search at a significantly lower search speed. In this case, for the search at low
15 speed, the invention makes use of the fact that in the case of recording digital television signals, each individual slanted track is numbered, in which case - in accordance with the D-VHS system standard - the respective track number is arranged in an area of the
20 respective slanted track called a "subcode area".

For ascertaining track-accurate tape positions by reading the slanted track numbering - in each case at the beginning of a search according to the invention and then upon reaching the respective target position
25 or the vicinity thereof - the normal reproduction mode of a video recorder of this type can advantageously be utilized.

Instead of the track numbering - or together with the track numbering - the invention also allows the use
30 of an optional time coding which - in accordance with the D-VHS system standard - is provided either in the "subcode area" or in the "main-code area" of a slanted track.

The invention additionally has the advantages that
35 it manages without marking of CTL pulses and can be realized in conjunction with a microprocessor that is present in any case in video recorders of this type, given appropriate supplementation and/or amendment of

the software, and so no additional outlay on circuitry is required.

Further advantages and developments emerge from the description below and from the claims.

5

BRIEF DESCRIPTION OF THE DRAWINGS

The invention is explained in more detail using an exemplary embodiment. In the figures:

- 10 Figure 1 shows a D-VHS video recorder according to the invention;
- Figure 2 shows a speed/time diagram of the search mode according to the invention for this video recorder, and
- 15 Figure 3 shows a flow diagram for the search mode in accordance with Figure 2.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

- 20 Figure 1 shows a D-VHS video recorder, called apparatus 1 hereinafter, in which blocks and arrows are used to illustrate in a symbol-like manner the elements and signals which are essential to the invention, in which case - in a manner known per se - a recording
- 25 medium in tape form for digital television signals, called tape 2 hereinafter, which is mounted in a cassette (not illustrated) has been drawn out of the cassette and is in engagement with a head drum 3, in order to be scanned by means of rotating read/write
- 30 heads. Means which are known per se are used for driving tape 2 (by means of capstan 4, head drum 3, and tape reels 5) and for the respective control of head drum and tape drives and tape winding device. Therefore, these means will be discussed only in so far
- 35 as is necessary for explaining the search mode according to the invention. The search mode is described below with reference to diagrams (Figure 2 and Figure 3).

Figure 2 diagrammatically shows the speed characteristic v_{tape} of the tape 2 as a function of the time t in the apparatus operating mode "search" for a recorded digital television signal. According to the invention, this search can be broken down into a plurality of successive time periods or steps:

In a first time period t_0-t_1 , a remote control (not illustrated) or the apparatus control device is used to input a stop time which is intended to correspond to the picture content to be sought, or to a predetermined slanted track.

In a second time period t_1-t_2 , the "reproduction" apparatus operating mode is used to determine a tape position as start position for the actual search, by determining the number of an arbitrary slanted track. This may be e.g. that slanted track whose number is detected first. In accordance with the D-VHS system standard, this slanted track can be assigned a corresponding CTL pulse in the CTL signal, which, in a manner known per se, is read by a stationary CTL read/write head 6 and fed to a microprocessor μP for evaluation. According to the invention, the said CTL pulse is utilized as reference signal for the start position of the actual search, which is intended to be characterized by acceleration of the tape transport to a relatively high speed v_2 (at the instant t_3), holding of the tape transport at this speed v_2 (corresponding to a fourth time period t_3-t_4), deceleration of the tape transport to a relatively low speed v_1 (corresponding to a fifth time period t_4-t_5) and moving to the target position at this tape transport speed v_1 (corresponding to a sixth time period t_5-t_6). In this case, the high speed v_2 is preferably intended to correspond to the customary rewind speed in video recorders.

Thus, as soon (i.e. at the instant t_2) as a slanted track has been detected using the slanted track numbering, the microprocessor μP stops the tape drive and carries out (in the third time period t_2-t_3) a calculation for the actual search, corresponding

control data of the apparatus 1 being determined up to the stop position at the end of the search according to the invention.

As mentioned above, however, the actual search for
5 its part encompasses the fourth, fifth and sixth time periods, in the fourth time period t_3-t_4 the tape 2 being moved at the correspondingly high speed v_2 relative to the "reproduction" apparatus operating mode. The fifth time period t_4-t_5 is arranged in the
10 vicinity of the target position of the search according to the invention and is characterized by deceleration of the tape transport to the speed v_1 , which is practically intended to correspond to the tape speed in the "reproduction" apparatus operating mode. The
15 deceleration can be carried out by means of the braking device of the apparatus 1 and/or by a changeover to the "reproduction" apparatus operating mode.

By virtue of this reduction in the speed at which the tape 2 is now transported from one tape reel 5 to
20 the other tape reel 5, the slanted track numbering becomes readable, with the result that track-accurate moving to the target position is ultimately achieved - by means of evaluating the slanted track numbering.

A coding/decoding device called a CODEC is used
25 for decoding the digital data stream (in the sixth time period t_5-t_6 and also already in the second time period t_1-t_2). The decoded data stream is fed to the microprocessor μP for evaluation of the data relevant to the search according to the invention and signal
30 processing resulting from this in conjunction with corresponding controls of the devices of the apparatus 1 which are involved in the sequence of the search mode according to the invention.

A time window or the like is preferably provided
35 for the beginning of the deceleration from the speed v_2 to the speed v_1 .

With regard to the beginning for deceleration, a function for a residual tape determination that is provided in any case in the apparatus 1 can

advantageously be used for an error correction: e.g. - depending on the realized embodiment of the apparatus with regard to the search mode according to the invention - in the case of counting errors with regard to the CTL pulse train, on account of counting errors of a tape counter connected to the tape winding device and/or on account of so-called "dropout" points on the tape 2, which do not permit any recording and hence any detection of CTL pulses.

10 In the case where, with the recording of a digital television signal, a corresponding time coding is assigned to the respective slanted tracks (as provided e.g. in accordance with the D-VHS system standard), the time code of an arbitrary slanted track which can be
15 detected first is preferably used as start position for the search according to the invention during the first time period t_0-t_1 , in order then to control the actual search during the fourth time period t_3-t_4 by means of the microprocessor μP , preferably by counting
20 successive CTL pulses.

In the case where, with the recording of a digital television signal, no corresponding time coding should be assigned to the respective slanted tracks, the number of the slanted track detected first during the
25 first time period t_0-t_1 is preferably used as start position for the search according to the invention, in order then to control the actual search during the fourth time period t_3-t_4 by means of the microprocessor μP , by counting successive CTL pulses.

30 With regard to further embodiments, instead of counting successive CTL pulses during the fourth time period t_3-t_4 , it is also possible to use the respective tape counter that is customary in apparatuses 1 of this type.

35 Figure 3 illustrates the search mode according to the invention performed by the apparatus 1 using a flow diagram.

After the start in accordance with block 100 (e.g. by actuation of a corresponding key on the remote

control of the apparatus), in accordance with block 101 (e.g. upon actuation of corresponding further keys on the remote control of the apparatus) the stop time for the search is specified, which is intended to correspond to the picture content to be sought, or to a predetermined slanted track. In accordance with block 102, the "reproduction" apparatus operating mode is used to effect processing of the digital data stream read by the head drum 3, in order, in accordance with block 103, to determine a tape position as start position for the actual search, the time code of an arbitrary slanted track which is detected first preferably being determined as start position or start time for the actual search. As soon as the time code has been determined, in accordance with block 104 the tape drive is stopped in order to calculate the number of CTL pulses which is necessary until the deceleration of the tape transport in the vicinity of the target position from the speed v_2 to the speed v_1 . As soon as this number of CTL pulses has been determined, in accordance with block 105 the actual search is started by the tape transport being accelerated to the speed v_2 , which, for example, may at the same time be the speed provided for the rewind mode of the apparatus 1. In accordance with blocks 106 and 107, detected CTL pulses are counted in conjunction with continuous evaluation of the instantaneous counting result, in which case - as is intended to be illustrated by the return to block 106 - the tape transport speed v_2 is maintained until correspondence with the value calculated in block 104 is ascertained.

With correspondence having been ascertained, in accordance with block 108 the tape transport speed v_2 is reduced by deceleration to the tape transport speed v_1 corresponding to the "reproduction" apparatus operating mode, with the result that the slanted track numbering becomes readable in order then to move to the target position with track accuracy by means of evaluating the slanted track numbering.